

- ※ Constant Voltage and Constant Current Operation
- ※ Excellent Line, Load and Ripple Specifications
- ※ 3 digit red LED Display of Voltage and Current
- ※ Coarse and Fine Voltage Controls
- ※ High Efficient Power
- ※ Short Circuit and Overload Protection



MODELS

MODEL	OUTPUT
PS1230	0-12V / 0-30A : single
PS1820	0-18V / 0-20A : single
PS3610	0-36V / 0-10A : single
PS6006	0-60V / 0-6A : single

Remote Sensing Application

		PS1230	PS1820	PS2415	PS3610	PS1230
Output	Voltage	0~12V	0~18V	0~24V	0~36V	0~60V
	Current	0~30A	0~20A	0~15A	0~10A	0~6A
	Power	360W	360W	360W	360W	360W
Line Regulation	Voltage	5mV	5mV	5mV	5mV	5mV
	Current	3mA	3mA	3mA	3mA	3mA
Load Regulation	Voltage	5mV	5mV	5mV	5mV	5mV
	Current	3mA	3mA	3mA	3mA	3mA
Meter Accuracy	Voltage	±(0.5%rdg + 2digits)				
	Current	±(0.5%rdg + 2digits)				
Noise & Ripple (Load Max)	Voltage (p-p)	100mV	100mV	100mV	100mV	100mV
	Voltage (rms)	5mV	5mV	5mV	5mV	5mV
	Current (rms)	5mA	5mA	5mA	5mA	5mA
Dimensions	Width x Height x Depth	138 x 162 x 290 (mm)				
Accessories	Instruction Manual, Power Cable, Test Leads, Spare Fuse					

Innovative Energies Limited, PO Box 19 501, Auckland 7, New Zealand.

1 Heremai Street, Henderson, Auckland. Phone +64 9 835 0700 Facsimile +64 9 837 3446
 email: info@innovative.co.nz www.innovative.co.nz